



voodoo lab pedal power mods

H.O. (High Output) modification of the Pedal Power

- There are 3 (so far) versions of the Pedal Power. (PP1, PP2 and PP2+)
- PP1 is very different from PP2 and PP2+
- Circuit-wise the PP2 and PP2+ are the same. Except the PP2+ has Heavy Duty voltage regulators for the Line6 (L6) outlets. (5 & 6 only). PP2 has the same small (100ma. Max.) regulators for all 8 of it's outlets.
- All PP1's will need their own H.O. (High Output) mods to power an echoczar properly. These mods are available for outlets 1 & 2 and outlets 7 & 8. NOTE: the DIP switch will Not be operational on the modded H.O. outlets.
- All PP2's will need Heavy Duty regulators installed on outlets 5 & 6 to even properly power Line6 products. NOTE: this mod transforms a PP2 into a PP2+. If powering Both a Line6 product, and an echoczar, outlets 1 & 2 can also receive H.O. mods. NOTE: the DIP switch remains operational after H.O. mods. To power the echoczar, place the DIP switch in the "NORMAL" position.
- All PP2+ Do Not need mods, IF the L6 outlets (5 & 6) are used with a "Y" power cable, and the DIP switch is in the "NORMAL" position. NOTE: if a Line6 product is to be used, outlets 1 & 2 may still receive the H.O. mods, and the echoczar may be powered from outlets 1 & 2, with a "Y" power cable. (again- place the DIP switch in the NORMAL position).
- The H.O. mods are rated at 185ma. @ 18v dc for "Y" cable use. This rating is conservative, based on continuous output with no "cool down".

features